

Analog Multimeter

YX-360 TRE-B



Features:

- Analog Multimeter with Mirror Scale
- Inbuilt Buzzer and LED
- 0Ω Adjustable with x 100 Range
- Transistor Test ,hFE with Diode



Technical Data :

Basic Functions	Range	Basic Accuracy of FSD	Sensitivity
DC Voltage	0.1mV~1000v	3; for 1000V:5	20kΩ/V
AC Voltage	10V~1000v	4; for 1000V:5	9kΩ/V
DC Current	50μA~10A	3; for 10A:5	
Resistance x 1	0.2Ω~2kΩ	3	
x 10	2Ω~20kΩ		
x 100	20Ω~200kΩ		
X 1k	200Ω~2MΩ		
X 10k	2kΩ~2Mhz		
Iceo	150 μA-15mA-150mA		
hFE	0~1000 with connector		

Special Function:

Diode Test	✓	Function Protection	✓
Transistor Testing	✓	Continuity Buzzer	About 100Ω

- **Standard Accessories** : Test Leads, Holster, Manual
- **Dimension** : 148(H) x 100(W) x 35(D)mm