

Lux Meter

LX-103



Features:

- Large Range up to 200000Lux
- Large LCD Display with Back Light and Bar Graph
- Auto Power Off
- MAX/MIN and Data Hold



Technical Data :

Basic Functions	Range	Resolution	Basic Accuracy
Measurement Range	0~200000Lux/ 0~20000FC	0.01Lux/0.01FC	+3%

Display	2000 counts	Analog Bar Indication	√
Auto Range	√	Manual Range	√
Auto Power Off	√	MAX/MIN Function	√
Relative Measurement	√	Peak Measurement	√
FC/Lux Unit Selection	√	Data Hold	√
Display Backlight	√	Low Battery indication	√

- **Standard Accessory** : Battery, Carry Case & Manual
- **Dimension** : 170mm x 89mm x 43mm